


## ▪ internet radio

---

### Quick Start Manual (사용 설명서)

# TENTATIVE



Internet radio service powered by opencast.co.kr



**Quick start manual** is dedicated to helping you configure and operate all aspect of internet radio.

**NTI Comodo Inc**

[www.nticomodo.com](http://www.nticomodo.com)

# ▪ INDEX

---

INDEX	page
1. Out look	-1-
2. How to set up	-2-
3. Remote controller	-4-
4. Quick operation	-5-
5. Specification	-6-
6. Utility tool	-7-
7. G1/2/3 Station group	-9-
8. Appendix 1 Recovery System	-11-
9. Appendix 2 Short form Ch. Info	-12-




# ■ Out look

## 1. Internet radio retail package

The internet radio retail package consist are;


- . Internet radio
- . LAN Cable RJ-45 UDP
- . AD/DC Adaptor DC5.0V 300mA
- . IR Remote controller
- . Stereo Earphone
- . User Manual – Korean/English



## 2. Internet radio Out look

The internet radio interface are;

- . RJ45 LAN JACK : UDP Cable
- . DC Power Jack : DC 5V 300mA
- . D-SUB9 Connector : **Reserved to maintenance at Factory Test only**
- . 3.5 mm(1/8") Stereo Headphone Jack
- . IR Remote SENSOR :38KHz IR receiver
- . Reset Switch : Recovery or firmware upgrade



# ■ Installation

## 3. Internet radio Standard set up configuration

The standard set up configuration is as follow figure 1 described how to set up internet radio . You may to prepare INTERNET MODEM. broadband internet connection required for internet radio service.




Figure-1 Standard Internet radio set up

## 4. Internet radio customer set up configuration

The customer set up configuration is as follow figure 2 described how to set up internet radio. The Stereo headphone out, it can be extend to connect an external device such as Hi-fi audio amplifier with dynamic speaker system.





Figure-2 Customer internet radio set up


# ■ Installation

## 5. Internet radio Set up and Boot load


### Step1, Boot loading



DHCP IP Set\*



Firmware version



Loading memory

#### Notice\*




IP Setting : The internet radio support DHCP/Static/PPPoE connection. Default IP set mode is DHCP. Please see [utility tool on page 7](#), Described how to internet radio IP configuration.

### Step2, How to select radio station ?



1. Press numeric number  
Example ) 100 channel

Remote controller numeric key  
press 1 + 0 + 0



2. Loading station- channel #100  
It will take few second depend on  
internet connection speed

3. Radio station audio automatically  
start playback, and listen headphone

#### Notice


There are 3 radio station group 1)G1 free radio station, 2) G2 music station and 3)G3 user define station group in a internet radio. Please see on [page 4](#) internet radio group select key information and on [page 9](#) described more information of G1/2/3 station group

### Step3, How to Playback volume control ?

The volume level control range 32 step from 0(zero) to 32 by IR remote controller




Press +/- key at IR remote controller



# ■ Remote Controller

## 6. Quick guide IR Remote controller operation



### \*Group select key notice

**G1:** Free station group – opencast provide free radio station channel up to 999 stations  
The station list will update without notice, please visit opncast website at <http://opencast.co.kr>

**G2:** Commercial music group – opencast provide music station channel up to 999 stations  
This G2 music station required registration. Please contact your local representative

**G3:** user defined station group – its empty channel for user defined channel station.  
Example, the user can figure out favorite internet radio station by utility software

## ■ Quick Operation

### 7. Quick Operating Table – Remote controller

Please see below table is described quick operating remote controller.

Function	Description		
IP Set up	IP Configuration tool	Openradio.exe Visit website and download tool	
Station group (See page 9)	Group1 IR Remote key  Free station 999ch	Group2 IR Remote key  Commercial 999 ch	Group3 IR Remote key  User define 999 ch
Power on/off	Press power key, toggle on/off 		
Channel up/down	Increase press + key at IR REMOTE decrease press – key at IR REMOTE		
Volume up/down	Increase press + key at IR REMOTE decrease press – key at IR REMOTE		
Sound mute on/off	Press “mute” key Sound mute toggle on/off		

### 8. Display 3 Digit alpha-numeric error message table

The internet radio 3 digit LED alphanumeric display indicate error message as follows;

Display 3 digit	Description
E01	Internet connection is not available. Please check modem or ISP
E02	Stream server is not available or not response
not	The station is not available; Stream Server is working or stop broadcasting
Lod	Loading memory/ or receiving stream data
Loc	The internet radio expired service

# ■ Specification

## 9. Specification


The internet radio device allow to use indoor/or office only. if more information, please contact opencast sales office/representative.

### Absolute maximum Ratings

Supply Voltage                      5.0V DC  
 Power consumption                300mA  
 Temperature Range                -40 ~ +85

Technical specification			
Stream format	2ch (Left/Right) 18 bit resolution	MP3	Up to 48K sample 320K bit rate
		WMA	Up to 48K sample 192K bit rate
Network interface	Ethernet RJ-45 DHCP/STATIC/PPPOE		
Network Security	none		
Audio Interface/output	Headphone out 1/8 " Full scale 1.5Vpp output Voltage		
Power supply	DC 5V 300mA external power adaptor		
Dimensions	110 mm x 110 mm x 22 mm Metal case - aluminum		
Weight	Net g	Full retail package g	
	Firmware		
Opencast RTOS upgradeable to ensure that latest capabilities and service can be offered on your opencast internet radio 2008-Nov : First release firmware version 1.0			
Requirement	Router	Router with wired 10/100 RJ-45 Ethernet connection Broadband internet connection required	
	NAS Device	Upnp compatible hardware (Upnp Server)	
Internet Radio Service	Shoutcast Server		
Display/Indicator	3 Digits 7-segment FND (Alpha-numeric display)		

### Recommend



# Utility tool

## 10. IP Configuration tool

The IP configuration tool is utility software that support to set IP configure in your internet radio device.


- openradio.exe : for internet radio general user (downloadable from website at [www.opencast.co.kr](http://www.opencast.co.kr))
- openradio\_admin.exe : enterprise/representative only (contact opencast sales/representative)

Openradio.exe screen shot (Korean)



### IP Configuration tool support

- 1) Set IP – STATIC/ DHCP/PPPoE
- 2) Available IP setting with multi internet radio device that connected local Ethernet router



## Utility tool

### 11. How to add new internet radio station at Group 3 user define station list?

**Notice: please set up internet radio device before you execute tool.**

- 1) Click **라디오검색** button
- 2) Search progress bar indicate and display Mac Address/F/W Version of device.
- 3) Display IP mode and Address

Add New internet radio station URL (support protocol http:// and mms:// )

Step 1: Click Internet radio device ( listing Mac Address as many as connected same router)

Step 2: Select target device which you add new station

Step 3: Input Station name and URL

Step 4: Save current new internet radio station click 

More information, [please refer to appendix2 – G3 User define 999 station](#)



#### How to listen my new added internet radio station

- 1) After save and stored new station, the internet radio device will reset automatically.
- 2) Press G3 key at Remote controller and select G3 station list
- 3) Select channel Number, It will be loading and start playback if you correct URL.

Notice

Do not input station URL as **http://abc.123.com/listen.pls**

Required URL address with stream server port no.

#### Example correct URL format

http://sc01.jukeon.com:8010


mms://211,43.217.85/fm\_live

http://www.rthk.org.hk/live1.asx

## ■ G1/G2/G3 Station Group

### 12. Over view - Internet radio station Group information

The internet radio have 3 station groups internal memory as G1 group is free radio station list, G2 is commercial music station group and G3 is user define station group.



### Highlight of internet radio group

**G1 group** : 24 hr internet radio station – Korean live broadcast station

All type of world – US, Japanese, Chinese, Spanish etc

G1 group support up to 999 stations – it will up-to-date list of station without notice

**G2 group** : 24 hr oversea radio station – Generic, oldies, country, dance, electronic, Rock, Jazz etc

G2 group support up to 999 stations – its will up-to-date list of station without notice,

**G3 group** : internet radio user can be set up to 999 station. Required utility tool

Support your favorite internet radio station list and figure out your own station channel.

### Example) How to turn on G1 group and select a channel?



Step 1: Press Group Key(G1) at IR remote controller



Step 2: Internet radio 3digit indicated **P-1**



Step 3: Select channel ex) 001 Korean SBS POWER FM

press +/- ch up/down key, 1 step channel up/down

## ■ G1/G2/G3 Station Group

### 13. Description - Internet radio station Groups

Group	Descriptions	Remark
<b>G1</b> <b>Free</b> internet radio	<b>Highlight</b> 24hr Korean live station –private live DJ K-POP:가요/종합/댄스/팝/뉴 에이지 등 Korean broadcast : 아리랑/극동/지역방송국 외 All type of world USA/Aust/Spain/England/Mexico/China/Japan Eerope/Asia/America/Oceania	<b>Free radio station</b> Provide Korean station by opencast Generic – Kpop, Jpop, Chinese etc Recommend – Interested in Korean and Korean popular music Please visit website and see detail of station list.(www.opencast.co.kr)
<b>G2</b> <b>Commercial</b> Music station	<b>Highlight</b> Most of popular internet radio station. Generic – Pop, dance, jazz, country etc All type of world	<b>Free radio station.</b> Provide oversea station by opencast Generic –pop, pop, Chinese etc All type of world Please visit website and see detail of station list. (www.opencast.co.kr)
<b>G3</b> <b>User</b> defined station	G3 station group is empty. Allowing to add your favorite internet radio station by yourself.  Maximum capacity is up to 999 stations	Required PC Utility software Please visit website and download <b>Openradio.exe</b>
<b>Notice</b>	<b>G1 Station list will be changed without notice.</b>  We actively encourage our users and listeners to suggest new stations to be added to our service. Allows you suggest us a new Internet radio station for inclusion in the Open Radio stations list database. Also recommend updates to our Existing stations list.	There is no charge for this service. Please mailing us at comodomusic@paran.com And including your information as followings; Your name[이름] e-mail address[이메일주소] Station name[방송국 이름] Station URL[방송 주소] Category [장르] Country[국가] web page[홈페이지] Additional information[기타]

#### Document History

2008/Nov : First released - tentative

By David Yoon  
 Internet radio device R&D Lab  
 NTI Comodo Inc

**END**


• Appendix1 – Recovery internet radio system

---

**The internet radio system support to recover factory rescue recovered by RESET function.**

**How to recover my internet radio?**

**1. Required special sharp tool – example) needle, paper clip etc**




Push reset switch and the device to start recovery as followings;

- 1) Turn off Display indicator
- 2) Restore data – to checking IP mode and setting up
- 3) Device Firmware version - if new version available, it will be upgrade automatically.
- 4) Downloading configuration and other information
- 5) Successfully recovered – turn on radio with latest mode  
(what you selected station and channel no)

**2. Plug out DC adaptor from internet radio device**

More simple way to upgrade firmware and channel information, The user allow to plug out DC adaptor and plug in again. It is similar to push reset switch and system recovery



## • Appendix2 - Internet radio channel information table

인터넷 라디오 채널 요약 정보 입니다. 상세한 채널 정보를 보시려면 홈페이지 [www.opencast.co.kr](http://www.opencast.co.kr)를 방문하시기 바랍니다. This short form table of internet radio channel described limited, If you need more information please visit web site at <http://opencat.co.kr> then we can better serve you.

아래의 정보는 인터넷 라디오 서비스 오픈 캐스트 에서 제공하는 채널 정보로써, 라이선스 계약에 의하여 제공되는 채널이며, 채널 제공자, 콘텐츠 제작자, 네트워크 전송권 등 일체의 정보는 법적으로 보호 의무가 있습니다. 임의로 복사 이동 저장 등 무단 사용시 법적 처벌을 받을 수 있습니다.

Group	Ch. no	Description	Remark
<b>G1 무료 인터넷 라디오 한국 채널 안내 – Korean internet radio station</b>			
G1 Free 999 Station	Now available ch.no 001 ~ 185	[FM radio] Korean FM radio broadcasting	Korean FM radio
		[팝] Private music broadcast station – pop ch	Private music station
		[트로트] Private music broadcast station - Korean popular song	Private music station
		[종합] Private music broadcast station – Korean hit song	Private music station
		[댄스] Private music broadcast station – Dance/remix	Private music station
		[뉴에이지] Private music broadcast station – New age	Private music station
		[개인 ] Private music broadcast station	
	[가요] Korean hit song ch		
	<b>186 ~ 999</b>	<b>Reserved. Ch 999 reserved for open radio Test/demo</b>	
<b>G2 무료 인터넷 라디오 해외 채널 안내 – Oversea internet radio station</b>			
G2 Free 999 Station	Now available ch.no 001 ~ 229	Today's Dance, Dance Hits	-
		50s, 60s, 70s, 80s Channel	-
		Country Hits, Acappella	-
		Electronica, Christmas, Smooth Jazz	-
		Beats, Classic Country, Disco	-
		Classic Hits,	-
		Australia, Mexico, US, Spain, Japan, Hong Kong etc	-
		Classic Rock, Disco Classics	-
	European Trance, Techno	-	
	<b>230 ~ 999</b>	<b>Reserved. Ch 999 reserved for open radio Test/demo</b>	-
<b>G3 사용자 정의 형 채널 입니다 – Allow to user define eg, add your favorite internet radio station URL</b>			
G3 User 999 Station	001 ~ 999	User define station list – Required utility tool software	Openradio.exe
	Stream URL	Support protocol 1)HTTP:// 2) MMS://	
	Audio file	Support stream playback WMA, MP3 Type of audio file	Stream audio file Stream media server
	Window media	Ex) Stream URL mms://abc.123.com/abc	
	Shout cast	Ex) Stream URL http://abc.123.com:8000	
	Stream file	Ex) http://opencast.co.kr/download/audiobook/sample04.mp3	
<b>Notice.</b>			
1) The channel list changed without notice. Please visit web site at <a href="http://opencast.co.kr">http://opencast.co.kr</a> to get latest channel information.			
2) G2 Commercial music 999 station required registration. Please contact local representative or mailing us at <a href="mailto:comodomusic@paran.com">comodomusic@paran.com</a> then we can better serve you.			
2) G3 User 999 Station list – The G3 channel group reserved for user defined such as stored your favorite internet radio station			